

Pet Friendly PIR Motion Sensor

Model: EPIR

1. BEFORE INSTALLATION

- Read the instructions thoroughly
- Remove the Sensor from the packaging
- Consider the most appropriate positioning for the PIR
- Avoid mounting the sensor near metal objects or electrical wiring

2. FEATURES


Two Lens PIR: pet tolerant to 25kgs.

With a vertical and horizontal detection range of 8m/110°.

Automatic temperature compensation and anti-air turbulence technology control: automatically adapts to environmental changes, thereby saving energy.

Automatic SMS notification of a low battery condition when connected to an ERA GSM Alarm System.

3. GET TO KNOW YOUR PRODUCT



- Detection Window
- Status Indicator
- Test Button

- Bracket Slot
- Self-adhesive Fixing Markers

KIT CONTENT

- Pet Friendly PIR Motion Sensor x 1
- 1.5V AA Batteries x 2
- Fixing Screws x 2
- Wall Bracket x 1
- Installation and Operating Manual x 1

4. LED INDICATION


Flashes every 2 seconds: Self-testing state.

Flashes twice: Self-testing is finished, enters working mode.

Flashes once: Movement is detected.

Flashes once every 3 seconds: Low battery indication (immediate battery change recommended). If the PIR is connected to an ERA GSM Alarm System, a SMS alert will automatically be sent to the registered user.

5. PCB LAYOUT



Infrared Sensor: Detects movement and triggers and alarm signal when the system is armed.

Tamper Switch: If the casing is opened when in 'working state' the tamper switch will be triggered and generate an alarm signal.